



Force Sensing Resistors

Global human machine interface (HMI) leader, Interlink Electronics—the originator of the Force Sensing Resistor* (FSR)—expands its signature line of sensors with the FSR X.

The improved design of the FSR X offers a greatly expanded dynamic sensing range that extends from 0.3N to 50N, providing enhanced precision and broadening the scope of the FSR X's potential applications.

The FSR X 400 series comprises a full range of models in various sizes, shapes, and configurations, all of which can be utilized for custom sensing solutions.

*Force Sensing Resistors are robust polymer thick film (PTF) devices that exhibit a decrease in resistance when increased force is applied to the surface of the sensor.

FEATURES

- Improved sensing range extends from 0.3N to 50N
- Ultrathin form factor
- · Able to withstand extreme temperatures and conditions
- Tested to 10 million actuations
- Simple and easy to integrate
- Customizable to a wide range of applications
- Cost effective

APPLICATIONS

- Industrial
- Robotics
- Medical
- Automotive
- Computing
- IoT
- Wearable Technology



Force Sensing Resistors

Device Characteristics

Sensor Resistance Output	Analog
Actuation Force	0.3N (min)
Force Sensing Range	0.3N – 50N
Force Repeatability Single Part	+/-2%
Force Repeatability Part to Part	+/-6% (Single Batch)
No-Load Resistance	>10 M~
Hysteresis	+5% (RF+ – RF-)/RF+
Long Term Drift @ 5kg, 10 days	<4% log ₁₀ (time)
Operating Temperature Performance	
Cold: -25°C after 1 hour Hot: +85°C after 1 hour	
Storage Temperature Performance	
Cold: -40°C after 120 hours Hot: +85°C after 120 hours	•
Tap Durability	
Tested to 10 Million actuations @1kg, 4Hz13% resistance change	
Thermal Shock @85°Cto -40°C, 20 Cycles +13% resistance change	
Standing Load Durability	
2.5kg for 24 hours	5% resistance change
ULAll materials UL grade 94 V-1 or better	
RoHS	Compliant

NOTES


- Specifications are derived from measurements obtained at 2,500 grams force, unless otherwise stated. Measurements are dependent on actuation interface, mechanism and measurement electronics.
- 2. The test was performed using FSR X[™] 402 design.
- 3. Additional information is available upon request.

Sensor Mechanical Data:


Active Area: Ø14.68mm

Nominal Thickness: 0.46mm

Switch Travel: 0.15mm



SECTION A-A LAYER STACK-UP



Contact Us

218, Building A, Branch 3, Life Science Park, Leibo Midtown Life Science Park, No. 22, Jinxiu East Road, Jinsha Community, Kengzi Street, Pingshan District, Shenzhen Phone: +18688839318 http://www.xyxfjy.com/ Sales & Support: andy_jiang@xyxfjy.com

Interlink Electronics reserves the right to make changes without further notice to any products or specifications herein and does not assume any responsibility or liability arising out of the application or use of any its products or circuits.

© 2019, Interlink Electronics, Inc. All rights reserved | REV1019